

# Surveillance Three Wire Earpiece with Acoustic Tube

> 1111ACP2200A



## Features

- > Separated microphone, PTT button and earpiece for discreet communication
- > Surgical grade acoustic tube; discreet and comfortable
- > Strong but flexible cable with Kevlar reinforcement
- > Optional ear mold allows ambient sounds
- > Designed for covert operation, where discreet communication is essential

## Technical Specification

### Speaker

|                       |                        |
|-----------------------|------------------------|
| Dimensions:           | $\Phi$ 16.2mm * 10.6mm |
| Impedance:            | 250 $\pm$ 500hm        |
| Sound Pressure Level: | 104 $\pm$ 3db @1000Hz  |

### Microphone

|                    |  |
|--------------------|--|
| Type:              | Electric Condenser Microphone          |
| Impedance:         | 2.2 kOhm                               |
| Sensitivity:       | -40 $\pm$ 3db @1000Hz<br>(0db = 1V/PA) |
| Operating Voltage: | 11.1-10VDC                             |

### PTT

|             |  |
|-------------|--|
| Dimensions: | $\Phi$ 14.8mm (Max),<br>52.5mm in length |
|-------------|--|

Call us now to find out more **0870 803 2233**  
or email the sales team: [sales@wirefr3.com](mailto:sales@wirefr3.com)

#### Wirefr3 Ltd

Berkhamsted House, 121 High Street  
Berkhamsted, Herts, HP4 2DJ

T: 0870 803 2233

E: [sales@wirefr3.com](mailto:sales@wirefr3.com)

[www.wirefr3.com](http://www.wirefr3.com)

> Connectors

|   | Product Code    | Description   |
|---|-----------------|---|
|    | 1111ACP2200AM1  | Surveillance three wire earpiece with acoustic tube with <b>Motorola Two-pin right angle</b> . Suitable for Motorola: GP300, CP040, XTN446, HYT: TC600.TC610/TC620, TC446   |
|    | 1111ACP2200AM1A | Surveillance three wire earpiece with acoustic tube with <b>Motorola Two-pin right angle</b> . Suitable for Motorola: XTNi and XTNiD  |
|    | 1111ACP2200AM4  | Surveillance three wire earpiece with acoustic tube with <b>Motorola multiple pin M4</b> . Suitable for Motorola: GP328, GP340, GP360, GP380  |
|    | 1111ACP2200AM5  | Surveillance three wire earpiece with acoustic tube with <b>Motorola multiple pin M5</b> . Suitable for Motorola: GP344, HYT: TC-780, TC3000; Kirisun: PT7200   |
|    | 1111ACP2200AM7  | Surveillance three wire earpiece with acoustic tube with <b>MOTOTRBO multiple pin</b> . Suitable for Motorola DP3400 / DP3600   |
|    | 1111ACP2200AK1  | Surveillance three wire earpiece with acoustic tube with <b>Kenwood two-pin</b> . Suitable for Kenwood: TK-2100, 2102, 2130, 2160, TK-3100, 3160, TK-3101, TK-3102, TK-3130   |
|   | 1111ACP2200AK2  | Surveillance three wire earpiece with acoustic tube with <b>Kenwood Multiple pin</b> . Suitable for Kenwood: TK-280, TK-290, TK-380, TK-385, TK-390, TK-480, TK-481, TK-2041, TK-2140, TK-3140, TK-3148   |
|  | 1111ACP2200AS2  | Surveillance three wire earpiece with acoustic tube with <b>Icom two pin right angle</b> . Suitable for Icom: IC-F3G, IC-F3GS, IC-G3GT, IC-F4G, IC-F4GS, ICF4GT, IC-F43GS, C-F43GT, IC-F43TR, IC-F11, IC-F11S, IC-F21, IC-F21S, IC-F31            |
|  | 1111ACP2200AS4  | Surveillance three wire earpiece with acoustic tube with <b>Icom multiple pin</b> . Suitable for Icom: IC-F50, IC-F51, IC-F60, IC-F61, IC-F30GS, IC-F3061, IC-F4061, IC-F3162, IC-F4162   |
|  | 1111ACP2200AY1  | Surveillance three wire earpiece with acoustic tube with <b>Yaesu/Vertex Standard One-Pin Right Angle 3.5mm Quadr.</b> Suitable for Vertex: VX-10, VX-110, VX-160, VX-180, VX-210, VX-210A, VX-200, VX-300, VX-400, VX-410, VX-420, VX-150, VX-2R |
|  | 1111ACP2200AY6  | Surveillance three wire earpiece with acoustic tube with <b>Yaesu/Vertex Standard Multiple-Pin</b> . Suitable for Vertex: VX-820, VX-821, VX-824, VX-829, VX-920, VX-921, VX-924, VX-929  |
| No image available  | 1111ACP2200AET1 | Surveillance three wire earpiece with acoustic tube with Entel <b>Suitable for Entel HX series:</b> HX402/403/405, 412/413/415, 422/423/425, 482/483/485  |
|  | 1111ACP2200AT1  | Surveillance three wire earpiece with acoustic tube with Tait <b>Suitable for Tait:</b> TP8110, TP8115, TP8120, TP8135, TP8140, TP7110  |

Call us now to find out more **0870 803 2233**  
or email the sales team: [sales@wirefr3.com](mailto:sales@wirefr3.com)