

# D Shaped Earpiece with Lapel Mic and Inline PTT

> 11DCH1040



## Features

- > Soft, skin-friendly ear hook material
- > Environmental PU cable reinforced with Kevlar
- > Suitable for many applications including; patrolling security personnel, hotel and catering staff, conference halls, restaurants and casinos etc

## Technical Specification

### Speaker

|                       |                          |
|-----------------------|--------------------------|
| Dimensions:           | $\Phi$ 15.0mm * 6.0mm    |
| Impedance:            | 320hm $\pm$ 15% @ 1000Hz |
| Rated Input Power:    | 100mW                    |
| Maximum Power:        | 200mW                    |
| Sound Pressure Level: | 105 $\pm$ 3db @1000Hz    |

### Microphone

|                    |  |
|--------------------|--|
| Type:              | Electric Condenser Microphone          |
| Impedance:         | 2.2 kOhm                               |
| Sensitivity:       | -40 $\pm$ 3db @1000Hz<br>(0db = 1V/PA) |
| Operating Voltage: | 11.1-10VDC                             |

### PTT

|             |                      |
|-------------|----------------------|
| Dimensions: | 34.9 * 14.2 * 11.8mm |
|-------------|----------------------|

Call us now to find out more **0870 803 2233**  
or email the sales team: [sales@wirefr3.com](mailto:sales@wirefr3.com)

#### Wirefr3 Ltd

Berkhamsted House, 121 High Street  
Berkhamsted, Herts, HP4 2DJ

T: 0870 803 2233

E: [sales@wirefr3.com](mailto:sales@wirefr3.com)

[www.wirefr3.com](http://www.wirefr3.com)

## > Connectors

|   | Product Code         | Description  |
|---|----------------------|--|
|    | 11DCH1040 <b>J6</b>  | D-shape earpiece with lapel Mic and Inline PTT with 3.5mm straight<br>Suitable for any radio or speaker Mic with 3.5mm audio jack  |
|    | 11DCH1040 <b>M2</b>  | D-shape earpiece with lapel Mic and Inline PTT with<br><b>Motorola two pin 2.5mm for T5.</b><br>Suitable for Motorola T5 series  |
|    | 11DCH1040 <b>M1</b>  | D-shape earpiece with lapel Mic and Inline PTT with<br><b>Motorola Two-pin right angle.</b> Suitable for Motorola:<br>GP300, CP040, XTN446, HYT: TC600.TC610/TC620,TC446   |
|    | 11DCH1040 <b>M1A</b> | D-shape earpiece with lapel Mic and Inline PTT with<br><b>Motorola Two-pin right angle.</b><br>Suitable for Motorola: XTNi and XTNiD   |
|    | 11DCH1040 <b>M4</b>  | D-shape earpiece with lapel Mic and Inline PTT with<br><b>Motorola multiple pin M4.</b><br>Suitable for Motorola: GP328, GP340, GP360, GP380   |
|    | 11DCH1040 <b>M5</b>  | D-shape earpiece with lapel Mic and Inline PTT with<br><b>Motorola multiple pin M5.</b> Suitable for Motorola: GP344,<br>HYT: TC-780, TC3000; Kirisun: PT7200  |
|   | 11DCH1040 <b>M7</b>  | D-shape earpiece with lapel Mic and Inline PTT with<br><b>MOTOTRBO multiple pin.</b><br>Suitable for Motorola DP3400 / DP3600  |
|  | 11DCH1040 <b>K1</b>  | D-shape earpiece with lapel Mic and Inline PTT with<br><b>Kenwood two-pin.</b> Suitable for Kenwood: TK-2100, 2102, 2130,<br>2160, TK-3100, 3160, TK-3101, TK-3102, TK-3130  |
|  | 11DCH1040 <b>K2</b>  | D-shape earpiece with lapel Mic and Inline PTT with<br><b>Kenwood Multiple pin.</b> Suitable for Kenwood: TK-280, TK-290, TK-380,<br>TK-385, TK-390, TK-480, TK-481, TK-2041, TK-2140, TK-3140, TK-3148  |
|  | 11DCH1040 <b>S2</b>  | D-shape earpiece with lapel Mic and Inline PTT with<br><b>Icom two pin right angle.</b> Suitable for Icom: IC-F3G, IC-F3GS,<br>IC-G3GT, IC-F4G, IC-F4GS, ICF4GT, IC-F43GS, C-F43GT, IC-F43TR,<br>IC-F11, IC-F11S, IC-F21, IC-F21S, IC-F31            |
|  | 11DCH1040 <b>S4</b>  | D-shape earpiece with lapel Mic and Inline PTT with<br><b>Icom multiple pin.</b> Suitable for Icom: IC-F50, IC-F51, IC-F60, IC-F61,<br>IC-F30GS, IC-F3061, IC-F4061, IC-F3162, IC-F4162  |
|  | 11DCH1040 <b>Y2</b>  | D-shape earpiece with lapel Mic and Inline PTT with<br><b>Yaesu/Vertex Standard One-Pin Right Angle with screw.</b><br>Suitable for Vertex: VX-10, VX-110, VX-160, VX-180, VX-210, VX-210A,<br>VX-200, VX-300, VX-400, VX-410, VX-420, VX-150, VX-2R |
|  | 11DCH1040 <b>Y6</b>  | D-shape earpiece with lapel Mic and Inline PTT with<br><b>Yaesu/Vertex Standard Multiple-Pin.</b> Suitable for Vertex: VX-820,<br>VX-821, VX-824, VX-829, VX-920, VX-921, VX-924, VX-929   |
| No image available  | 11DCH1040 <b>ET1</b> | D-shape earpiece with lapel Mic and Inline PTT with Entel<br><b>Suitable for Entel HX series:</b> HX402/403/405, 412/413/415,<br>422/423/425, 482/483/485  |
|  | 11DCH1040 <b>T1</b>  | D-shape earpiece with lapel Mic and Inline PTT with Tait<br><b>Suitable for Tait:</b> TP8110, TP8115, TP8120,<br>TP8135, TP8140, TP7110  |

Call us now to find out more **0870 803 2233**  
or email the sales team: [sales@wirefr3.com](mailto:sales@wirefr3.com)