

# Medium Duty Speaker Mic

> 11SPK3000



## Features

- > High clarity
- > Built in 3.5mm audio jack
- > Optional emergency button
- > Specially designed for security applications

## Technical Specification

### Speaker

|                       |                    |
|-----------------------|--------------------|
| Dimensions:           | Φ 45.0mm           |
| Impedance:            | 80hm ± 15% @1000Hz |
| Rated Input Power:    | 500mW              |
| Maximum Power:        | 1W                 |
| Sound Pressure Level: | 103 ± 4db @1000Hz  |

### Microphone

|                    |                                    |
|--------------------|------------------------------------|
| Type:              | Electric Condenser Microphone      |
| Impedance:         | 2.2 kOhm                           |
| Sensitivity:       | -36 ± 3db @1000Hz<br>(0db = 1V/PA) |
| Operating Voltage: | 1W                                 |

|           | Emergency Button | Audio Jack      | Wireless PPT |
|-----------|------------------|-----------------|--------------|
| 11SPK3000 | No               | Listen Only     | No           |
| 11SPK3001 | No               | Listen and Talk | No           |
| 11SPK3003 | Yes              | Listen and Talk | No           |

Call us now to find out more **0870 803 2233**  
or email the sales team: [sales@wirefr3.com](mailto:sales@wirefr3.com)

**Wirefr3 Ltd**  
Berkhamsted House, 121 High Street  
Berkhamsted, Herts, HP4 2DJ

T: 0870 803 2233  
E: [sales@wirefr3.com](mailto:sales@wirefr3.com)  
[www.wirefr3.com](http://www.wirefr3.com)

**wirefr3.com**  
Excellence in Wireless Communications

> Connectors

|   | Product Code | Description  |
|---|--------------|--|
|    | 11SPK3000M1  | Medium Duty Speaker Mic with <b>Motorola Two-pin right angle.</b> Suitable for Motorola: GP300, CP040, XTN446, HYT: TC600.TC610/TC620,TC446  |
|    | 11SPK3000M1A | Medium Duty Speaker Mic with <b>Motorola Two-pin right angle.</b> Suitable for Motorola: XTNi and XTNiD  |
|    | 11SPK3000M4  | Medium Duty Speaker Mic with <b>Motorola multiple pin M4.</b> Suitable for Motorola: GP328, GP340, GP360, GP380  |
|    | 11SPK3000M5  | Medium Duty Speaker Mic with <b>Motorola multiple pin M5.</b> Suitable for Motorola: GP344, HYT: TC-780, TC3000; Kirisun: PT7200   |
|    | 11SPK3000M7  | Medium Duty Speaker Mic with <b>MOTOTRBO multiple pin.</b> Suitable for Motorola DP3400 / DP3600   |
|    | 11SPK3000K1  | Medium Duty Speaker Mic with <b>Kenwood two-pin.</b> Suitable for Kenwood: TK-2100, 2102, 2130, 2160, TK-3100, 3160, TK-3101, TK-3102, TK-3130   |
|  | 11SPK3000K2  | Medium Duty Speaker Mic with <b>Kenwood Multiple pin.</b> Suitable for Kenwood: TK-280, TK-290, TK-380, TK-385, TK-390, TK-480, TK-481, TK-2041, TK-2140, TK-3140, TK-3148   |
|  | 11SPK3000S2  | Medium Duty Speaker Mic with <b>Icom two pin right angle.</b> Suitable for Icom: IC-F3G, IC-F3GS, IC-G3GT, IC-F4G, IC-F4GS, ICF4GT, IC-F43GS, C-F43GT, IC-F43TR, IC-F11, IC-F11S, IC-F21, IC-F21S, IC-F31            |
|  | 11SPK3000S4  | Medium Duty Speaker Mic with <b>Icom multiple pin.</b> Suitable for Icom: IC-F50, IC-F51, IC-F60, IC-F61, IC-F30GS, IC-F3061, IC-F4061, IC-F3162, IC-F4162   |
|  | 11SPK3000Y2  | Medium Duty Speaker Mic with <b>Yaesu/Vertex Standard One-Pin Right Angle with screw.</b> Suitable for Vertex: VX-10, VX-110, VX-160, VX-180, VX-210, VX-210A, VX-200, VX-300, VX-400, VX-410, VX-420, VX-150, VX-2R |
|  | 11SPK3000Y6  | Medium Duty Speaker Mic with <b>Yaesu/Vertex Standard Multiple-Pin.</b> Suitable for Vertex: VX-820, VX-821, VX-824, VX-829, VX-920, VX-921, VX-924, VX-929  |
| No image available  | 11SPK3000ET1 | Medium Duty Speaker Mic - Entel<br><b>Suitable for Entel HX series:</b> HX402/403/405, 412/413/415, 422/423/425, 482/483/485   |
|  | 11SPK3000T1  | Medium Duty Speaker Mic - Tait<br><b>Suitable for Tait:</b> TP8110, TP8115, TP8120, TP8135, TP8140, TP7110   |

Call us now to find out more **0870 803 2233**  
or email the sales team: [sales@wirefr3.com](mailto:sales@wirefr3.com)